

Available online at <http://www.mecs-press.net/ijem>

Performance Analysis, Controller Selection And Verification Of Electric Motor For Mechatronics Motion Control Applications, Using New MATLAB Built-In Function And Simulink Model

Ahmad A. Mahfouz ^{1,2}, Farhan A. Salem ^{2,3}

¹ *Department of Automatic and Mechatronics Systems, Vladimir State University, Vladimir, RF*

² *Mechatronics Sec. Dept. of Mechanical Engineering, Faculty of Engineering, Taif University, 888, Taif, Saudi Arabia*

³ *Alpha center for Engineering Studies and Technology Researches, Amman, Jordan*

Abstract

This paper proposes a new MATLAB built-in function, mathematical and simulink models, all to be simultaneously simple, user–friendly and to be used to face the two top challenges in developing mechatronic motion control systems, particularly, the early identifying system level problems and ensuring that all design requirements are met, as well as, to simplify and accelerate Mechatronics motion control design process including; performance analysis and verification of a given electric DC system, proper controller selection and verification for desired output speed or angle. The proposed models and function are intended for research purposes, application in educational process, and to be used by the mechatronics students and engineers for selection, design and verification purposes.

Index Terms: Mechatronics, electric Motor, control, built-in function, mathematical and simulink model.

© 2013 Published by MECS Publisher. Selection and/or peer review under responsibility of the Research Association of Modern Education and Computer Science.

1. Introduction

The term control system design refers to the process of selecting feedback gains that meet design specifications in a closed-loop control system. Most design methods are iterative, combining parameter selection with analysis, simulation, and insight into the dynamics of the plant [1][2]. Motion control is a sub-field of control engineering, in which the position or velocity of a given machine are controlled using some type of actuating machine. The accurate control of motion is a fundamental concern in mechatronics applications, where placing or moving an object in the exact desired location or with desired speed with the

* Corresponding author. Tel.: 00966; 533273146
E-mail address: salem_farh@yahoo.com

exact possible amount of force and torque at the correct exact time, while consuming minimum electric power, at minim cost, is essential for efficient system operation [3][4]. The actuating machines most used in mechatronics motion control systems are DC machines (motors), therefore motion control in mechatronics applications is simplified to a DC motor motion control. DC Motor and its features can be tested and analyzed both by control system design calculation and by MATLAB software, also by using a simple microcontroller of PIC micro, with corresponding control algorithm, the rotation of DC motor, that is the motion of load attached, can be controlled easily and smoothly. The main units of general motion control system are; input unit (sensor), control unit (e.g. PICmicro) and output unit and its drive (mainly DC motor).

To face the two top challenges in developing mechatronic motion control systems, particularly, the early identifying system level problems and ensuring that all design requirements are met, as well as , to simplify and accelerate Mechatronics motion control design process including; performance analysis of a given electric DC actuator system, proper controller selection, design and overall motion system verification for desired output speed or angle , We are to derive electric DC motor basic mathematical models, select the most applied and proper control strategies for DC motor motion control, with corresponding sensing devices, connect all in feedback and represent all into one general simulink model, also, since MATLAB is a powerful tool that can be used in control system analysis and design, however, We are to use MATLAB programming capabilities, to design a new MATLAB built-in function, to be simple and user friendly, to compare different control strategies in order to choose the best control strategy that can be applied to control the output angular position, θ and speed ω of a given PMDC motor, corresponding to applied input voltage V_{in} to meet desired performance specifications. The designed MATLAB program can be used to analyze the response of a given PMDC that can be used in mechatronics motion control applications e.g. robot arm or mobile robot.

2. System modeling

2.1 Modeling of the Permanent Magnet DC Motor

The PMDC motor is an example of electromechanical systems with electrical and mechanical components, a simplified equivalent representation of DC motor's two components and main application are shown in Figure 1.




Fig.1 (a) Schematic of a simplified equivalent representation of the DC motor's electromechanical components.




Fig.1(b) Schematic of a simplified motion of attached load to DC motor.

The transfer function of DC motor electric component relating input armature current, i_a and voltage V_{in} , can be derived by applying Kirchoff's law around the electrical loop by summing voltages throughout the R-L circuit, this gives Eq.(1), taking Laplace transform and rearranging gives Eq.(2):

$$\sum V = V_{in} - V_R - V_L - EMF = 0 \quad (1)$$

$$V_{in} = R * i_a + L_a \left(\frac{di_a}{dt} \right) + K_b \frac{d\theta}{dt} \Rightarrow (L_a s + R_a) I(s) = V_{in}(s) - K_b s \theta(s)$$

$$\frac{I_a(s)}{[V_{in}(s) - K_b \omega(s)]} = \left[\frac{1}{(L_a s + R_a)} \right] \quad (2)$$

Transfer function of PMDC motor mechanical component relating output torque, T_m and input rotor speed is derived by performing the energy balance; the sum of the torques must equal zero, we have Eq.(3) Substituting, and rearranging, we have Eq.(4):

$$\sum T = J * \alpha = J * d^2 \theta / dt^2 \quad (3)$$

$$T_e - T_\alpha - T_\omega - T_{EMF} = 0 \quad \text{At steady state, } i_a = T_\alpha + T_\omega + (T_{load} + T_f) \quad (4)$$

Where T_f : The coulomb, can be found at steady state, where derivatives are zero, to be[5]:

$$K_t * i_a - b * \omega = T_f \quad (5)$$

In the following calculation the disturbance torque, T , is all torques including coulomb friction, can be for

simplicity assumed zero , and T is given by; $T=T_{load}+T_f$. Substituting in Eq.(4) each of Eq.(5) and the following values: $T_e = K_t * i_a$, $T_\alpha = J_m * d^2\theta/dt^2$, $T_\omega = b_m * d\theta/dt$, and considering that in the open loop DC motor system without load attached, the change in T_{load} is zero gives:

$$K_t * i_a - T_{load} - J_m * d^2\theta/dt^2 - b_m * d\theta/dt = 0$$

Taking Laplace transform and rearranging gives:

$$K_t I(s) - T_{load} - \frac{1}{s^2} \theta(s) - b_m s \theta(s) = 0 \Leftrightarrow K_t I(s) - T_{load} = (J_m s + b_m) s \theta(s)$$

$$\frac{\omega(s)}{[K_t I_a(s) - T_{Load}(s)]} = \left[\frac{1}{(J_m s + b_m)} \right]$$

In case of no load attached, $T_{load} = 0$, we have:

$$\frac{\omega(s)}{[K_t I_a(s)]} = \left[\frac{1}{(J_m s + b_m)} \right] \quad (6)$$

The electrical and mechanical components of PMDC motor are coupled to each other through an algebraic torque equation given by:

$$Motor Torque = T_m = K_t * i_a \quad (7)$$

To derive the PMDC motor transfer function, we need to rearrange Eq.(2) describing electrical characteristics of PMDC, such that we have only $I(s)$ on the right side, then substitute this value of $I(s)$ in Eq.(6) describing PMDC mechanical characteristics, this all gives [4-6] :

$$I_a(s) = \left[\frac{1}{(L_a s + R_a)} \right] [V_{in}(s) - K_b \omega(s)] \Rightarrow K_t \left[\frac{1}{(L_a s + R_a)} \right] [V_{in}(s) - K_b \omega(s)] = J_m s^2 \theta(s) + b_m s \theta(s) \quad (8)$$

Rearranging Eq.(8) , we obtain the PMDC motor open loop transfer function without any load attached relating the input voltage, $V_{in}(s)$, to the motor shaft output angle, $\theta(s)$, given by:

$$G_{angle}(s) = \frac{\theta(s)}{V_{in}(s)} = \frac{K_t}{\left\{ s [(L_a s + R_a)(J_m s + b_m) + K_t K_b] \right\}} = \frac{K_t}{L_a J_m s^3 + (R_a J_m + b_m L_a) s^2 + (R_a b_m + K_t K_b) s} \quad (9)$$

The PMDC motor open loop transfer function relating the input voltage, $V_{in}(s)$, to the angular velocity, $\omega(s)$, given by:

$$G_{speed}(s) = \frac{\omega(s)}{V_{in}(s)} = \frac{K_t}{\left\{ [(L_a s + R_a)(J_m s + b_m) + K_t K_b] \right\}} = \frac{K_t}{L_a J_m s^2 + (R_a J_m + b_m L_a) s + (R_a b_m + K_t K_b)} \quad (10)$$

Here note that the transfer function Gangle(s) can be expressed as: Ga(s) =Gspeed(s) *(1/s) . This can be obtained using MATLAB, using the following, code [1]:

```
>> G_angle = tf(1,[1,0])* G_speed
```

Where: running tf(1,[1,0]), will return 1/s

3. Controller selection and design

The modern advances in electric motors and controllers improve motors speed, acceleration, controllability, and reliability; also allow designers a wider choice of power and torque. The term control system design refers to the process of selecting feedback gains that meet design specifications in a closed-loop control system. Most design methods are iterative, combining parameter selection with analysis, simulation, and insight into the dynamics of the plant [2]. There are many motor motion control strategies that may be more or less appropriate to a specific type of application each has its advantages and disadvantages. The designer must select the best one for specific application. In [2-3] most suitable control strategies for DC motor motion control, are suggested, were different control strategies were selected, designed, applied and their action were compared to select the most suitable control of a given DC motor in terms of output speed and angle. Most of these suggested control strategies will be applied in suggested system model, mainly PID, PI, PD as separate blocks to be applied with and without deadbeat response, also lead and lag compensators, the designer must select the best controller for specific application.

PID controller design: PID controllers are most used to regulate and direct many different types of dynamic plants the time-domain, The PID gains are to be designed and tuned to obtain the desired overall desired response. The PID controller transfer function is given by:

$$G_{PID} = K_p + \frac{K_I}{s} + K_D = \frac{K_D s^2 + K_p s + K_I}{s} = \frac{K_D \left[s^2 + \frac{K_p}{K_D} s + \frac{K_I}{K_D} \right]}{s} \quad (11)$$

Proportional -Integral (PI) - PI controller is widely used in variable speed applications and current regulation of electric motors, because of its simplicity and ease of design. PI controller transfer function is given by:

$$G_{PI}(s) = K_p + \frac{K_I}{s} = \frac{(K_p s + K_I)}{s} = \frac{K_p \left(s + \frac{K_I}{K_p} \right)}{s} = \frac{K_p (s + Z_o)}{s} \quad (12)$$

Where, Zo: Zero of the PI-controller, KP: The proportional gain, KPI: The proportional coefficient; TI: time constant. This transfer function, shows that, PI controller represents a pole located at the origin and a stable zero placed near the pole, at Zo= - KI/ KP, resulting in drastically eliminating steady state error due to the fact that the feedback control system type is increased by one.

Proportional -Derivative, PD controller: The transfer function of PD-controller is given by:

$$G_{PD}(s) = K_p + K_D s$$

Rearranging, we have the following form:

$$G_{PD}(s) = K_p + K_D s = K_D \left(s + \frac{K_p}{K_D} \right) = K_D (s + Z_{PD}) \Leftrightarrow Z_{PD} = \frac{K_p}{K_D} \quad (13)$$

The PD-controller is equivalent to the addition of a simple zero at Z_{PD} :

Lead compensator: Lead compensator is a soft approximation of PD-controller, The PD controller, given by $G_{PD}(s) = K_p + K_D s$, is not physically implementable, since it is not proper, and it would differentiate high frequency noise, thereby producing large swings in output, to avoid this, PD-controller is approximated to lead controller of the following form[6,7,8]:

$$G_{PD}(s) \approx G_{Lead}(s) = K_p + K_D \frac{Ps}{s+P}$$

The larger the value of P , the better the lead controller approximates PD control, rearranging gives:

$$G_{Lead}(s) = K_p + K_D \frac{Ps}{s+P} = \frac{K_p(s+P) + K_D Ps}{s+P}$$

$$G_{Lead}(s) = \frac{(K_p + K_D P)s + K_p P}{s+P} = (K_p + K_D P) \frac{s + \left[\frac{K_p P}{K_p + K_D P} \right]}{s+P}$$

Now, let $K_C = K_p + K_D P$ and $Z = K_p P / (K_p + K_D P)$, we obtain the following approximated controller transfer function of PD controller, and called lead compensator:

$$G(s) = K_C \frac{s+Z}{s+P}$$

If $Z < P$ this controller is called a lead controller (or lead compensator). If $Z > P$: this controller is called a lag controller (or lag compensator). The transfer function of lead compensator is given by:

$$G_{lead}(s) = K_c \frac{(s+Z_o)}{(s+P_o)}, \text{ where } : Z_o < P_o \quad (14)$$

Lag compensator; The Lag compensator is a soft approximation of PI controller, it is used to improve the steady state response, particularly, to reduce steady state error of the system, the reduction in the steady state error accomplished by adding equal numbers of poles and zeroes to a systems [7].

$$G_{PI}(s) \approx G_{lag}(s) = K_p + \frac{K_I}{s} = \frac{K_p s + K_I}{s} = K_p \frac{\left(s + \frac{K_I}{K_p} \right)}{s}$$

Since PI controller by it self is unstable, we approximate the PI controller by introducing value of P_o that is not zero but near zero; the smaller we make P_o , the better this controller approximates the PI controller,

$$G_{lag}(s) = K_c \frac{(s + Z_o)}{(s + P_o)} \quad (15)$$

Where: $Z_o > P_o$, and Z_o small numbers near zero and $Z_o = K_v/K_p$, the lag compensator zero. P_o : small number, The smaller we make P_o , the better this controller approximates the PI controller.

3.1 Sensors modelling: speed and position Sensors

The output motion of PMDC in terms of shaft position and speed, need to be measured and feedback to control system, to close the control loop. The sensing device used to measure and feedback the output actual position of the motor shaft, is potentiometer. The potentiometer output is proportional to the motor shaft angle, θ , The output voltage of potentiometer, V_{pot} is given by: $V_{pot} = \theta a * K_{pot}$. The potentiometer constant, K_{pot} equals the ratio of the voltage change to the corresponding angle change,

For robot arm, Potentiometer is used to measure the actual output arm position, θ_L , and convert it into corresponding volt, V_p and then feeding back this value to controller, the Potentiometer output is proportional to the actual robot arm position, θ_L . An applied voltage of 0 to 12 volts corresponds linearly to an output arm angle of 0 to 180, this gives the potentiometer constant, K_{pot} equals:

$$K_{pot} = \frac{\text{(Voltage change)}}{\text{(Degree change)}} = (12 - 0) / (180 - 0) = 0.0667 \text{ V / degree} \quad (16)$$

For mobile robot, Tachometer is used to measure the actual output angular speed, ω .. Dynamics of tachometer can be represented using Eq.(16), correspondingly, the transfer function of the tachometer is given by Eq.(17), We are to drive a given robotic platform system, using a given PMDC, with linear velocity of 0.5 m/s, the angular speed is obtained as: $\omega = V/r = 0.5 / 0.075 = 6.6667 \text{ Rad/s}$. Substituting values, we have Tachometer constant, given by Eq.(18):

$$V_{out}(t) = K_{tach} * \frac{d\theta(t)}{dt} = K_{tach} * \omega \Rightarrow K_{tach} = \frac{V_{out}(s)}{\omega(s)} \quad (17)$$

$$K_{tach} = \frac{12}{6.6667} = 1.8. \quad (18)$$

The following nominal values for the various parameters of a PMDC motor used : $V_{in}=12 \text{ Volts}$; $J_m=0.02 \text{ kg m}^2$; $b_m =0.03$; $K_t =0.023 \text{ N-m/A}$; $K_b =0.023 \text{ V-s/rad}$, $R_a =1 \text{ Ohm}$; and $L_a=0.23 \text{ Henry}$; $T_L=$ no load attached, gear ratio, $n=1:2$, and design criteria : applied voltage of $V_{in} = 0$ to 12 volts corresponds linearly to an output arm angle $\theta = 0$ to 180, $PO\% < 5\%$, $T_s < \text{less } 2 \text{ second}$, gain margin, $G_m > 20 \text{ dB}$, phase margin, $\Phi_m > 40 \text{ degrees}$, $\zeta = 0$. A negative feedback control system with forward controller shown in Figure 2(a)(b) is used




Fig.2 (a) Block diagram representation of PMDC motor control




Fig. 2 (b) Preliminary simulink model for negative feedback with forward compensation.

3.2 Simulink Model and built-in function

The derived transfer function can be used to build a simulink model show in Figure 3, this model has, allmostly, the same functions as the designed and proposed built-in function, where using manual switch designer can select controller type and output controlled variable (speed or angle) .

To simplify and accelerate the performance analysis of open loop motor system, as well as select and design a control system, a new MATLAB function is designed, named `pmdc` , this function is called by typing it in command window as any MATLAB built-in function, it has no input argument, when function is

called, first designer is asked to define used PMDC motor parameters, time vector for output speed and angle response and finally desired output both maximum angle (for position control application), and speed (for speed control application), in result built-in function will return , potentiometer constant, tachometer constant, PMDC motor open loop transfer function in terms of input voltage and output angle, output speed, and corresponding step, ramp parabolic responses , second designer is asked to select control system (Pro,D,I, PI,PD, PID, lag, lead ,lead integral), and corresponding gains values in row vector form , in result MATLAB will return the step response of output speed and angle , and display in both tabular and curve forms the system performance specifications with selected controller applied, Finally to select more suitable control system and compare applying any controller the program once again, ask user to select another controller type, and return the same result but for the new controller selected.

The selected control system response can by verified and once again evaluated, by defining the selected gains and zeros and running simulink model. To demonstrate how the proposed function works, the following nominal values of a given DC motor are to be used: $V_{in}= 12$; $J_m=0.02$; $b_m =0.03$; $K_t =0.023$; $K_b=0.023$; $R_a =1$; $L_a=0.23$; $T_L = 0$; maximum desired output angle=180 (in positron control) ;max desired output speed=6.6667 (motion control) ; potentiometer constant $K_{pot}=0.0667$; tachometer constant $K_{tach}=1.8$;

4. Demonstrations, testing and results.

Running the proposed built in function for given motor parameters and choosing time vector for output angle and speed responses to be correspondingly: [0:0.1:10] and [0:0.1:100], then by defining nominal values of used PMDC parameters and finally running the model, the model will return shown in Figure 4(a) open loop and closed loop PMDC system transfer functions and response curves, by studying and analyzing these curves we can see that both closed loop transfer functions in terms of both output angle and speed is type zero, with finite E_{ss} for step input, and infinity E_{ss} for both ramp and parabolic.

Now, selecting, PD controller and defining PD gains, for simplicity to be $K_p = [1 \ 2 \ 3]$, $K_d = [1 \ 2 \ 3]$, will result in step responses in terms of output speed and angle shown in Figure 4(b) and table of performance specifications values in terms of both output speed and angle shown below : next below is shown what will be seen in MATLAB command window when running the program and applying PD controller:

5. Design verification using new built-in function and simulink model;

To simplify and accelerate the performance analysis of open loop motor system, as well as select and design a control system, a new MATLAB function is designed, named `pmdc` , this function is called by typing it in command window as any MATLAB built-in function, it has no input argument, when function is called, first designer is asked to define used PMDC motor parameters, time vector for output speed and angle response and finally desired output both maximum angle(for position control application), and speed(for speed control application),, in result built-in function will return , potentiometer constant, tachometer constant, PMDC motor open loop transfer function in terms of input voltage and output angle then output speed, and corresponding step, ramp parabolic response , second designer is asked to select control system (Pro,D,I, PI,PD, PID, lag, lead ,lead integral), and corresponding gains values in row vector form ,and in result MATLAB will return the step response of output speed and angle , and display in both tabular and curve forms the system performance specifications after selected controller is applied, Finally to select more suitable control system and compare applying any controller the program once again. Ask used to select another controller type, and return the same result but for the new controller selected.

The selected control system response can by verified and once again evaluated, by defining the selected gains and zeros and running simulink model. To demonstrate how the proposed function works, the following nominal values of a given DC motor are to be used: $V_{in}= 12$; $J_m=0.02$; $b_m =0.03$; $K_t =0.023$; $K_b=0.023$; $R_a =1$; $L_a=0.23$; $T_L = 0$; maximum desired output angle=180 (in positron control) ;max desired output

speed=6.6667 (motion control) ; potentiometer constant Kpot =0.0667 ; tachometer constant Ktach=1.8;




Fig. 3 Block diagram representation of PMDC motor system, with

6. Demonstrations, testing and results.

Running the proposed built in function for given motor parameters and choosing time vector for output angle and speed responses to be correspondingly: [0:0.1:10] and [0:0.1:100], then by defining (entering) nominal values of used PMDC parameters and clicking enter, open loop and closed loop PMDC system transfer functions shown below and responses, shown in Figure 4(a) will be displayed, by studying these curves we can see that both closed loop transfer functions in terms of both output angle and speed is type zero, with finite E_{ss} for step input, and infinity E_{ss} for both ramp and parabolic.

Now, selecting, PD controller and defining PD gains, for simplicity to be $K_p = [1 \ 2 \ 3]$, $K_d = [1 \ 2 \ 3]$, will

result in step responses in terms of output speed and angle shown in Figure 4(b) and table of performance specifications values in terms of both output speed and angle shown below : next below is shown what will be seen in MATLAB command window when running the program and applying PD controller:

 Analysis and controller selection and evaluation of
 a given PMDC motor output Angle OR Speed :-Program

Define used PMDC motor parameters & desired output Data:

```
=====
```

Jm	bm	Kt	Ra	La	Desired output angle	Desired output speed	Kpot	Ktach
0.02	0.03	0.023	1	0.23	180	6.6667	0.0666667	1.79999

```
-----
```

Enter time vector for output speed response: [0:0.1:10]
 Enter time vector for angle output response: [0:0.1:10]
 =====

Open loop transfer function of original PMDC motor system relating Vin & angle:
 G(s) = 'Theta'(s)/Vin(s)=

$$\frac{0.023}{0.0046 s^3 + 0.0269 s^2 + 0.03053 s}$$

The closed loop Transfer function of PMDC motor system relating Vin & angle:
 Transfer function:

$$\frac{0.023}{0.0046 s^3 + 0.0269 s^2 + 0.03053 s + 0.001534}$$

```
=====
```

Open loop transfer function of original PMDC motor system relating Vin & speed:
 G(s) = 'Omega'(s)/Vin(s)=

$$\frac{0.023}{0.0046 s^2 + 0.0269 s + 0.03053}$$

The closed loop transfer function of PMDC motor system relating Vin & speed:
 T(s) = 'Omega'(s)/Vin(s)=

$$\frac{0.023}{0.0046 s^2 + 0.0269 s + 0.07193}$$

```
=====
```

Choose controller TYPE: Pro,D,I, PI,PD, PID, lag, lead ,lead integral :PD
 =====

Enter Proportional gain values in row vector form Kp = [1 2 3]
 Enter Derivative gain values in row vector form Kd = [1 2 3]
 =====

For chosen Kp,Kd the following ANGLE RESPONSE SPEC. results are obtained:
 =====

Gain Kp	Gain Kd	Error (Ess)	(Mp)	max Output Peak value	Final output
1.0000	1.0000	0.0900	-34.5487	145.4513	179.9100
2.0000	2.0000	0.0900	-0.3713	179.6287	179.9100
3.0000	3.0000	0.0900	-0.0900	179.9100	179.9100

For chosen Kp,Kd the following ANGLE RESPONSE SPEC. results are obtained:

Gain Kp	Gain Kd	Error (Ess1)	(Mp1) (Mul)	max value (Peak)	Final output
1.0000	1.0000	4.5913	-2.8035	3.8632	2.0754
2.0000	2.0000	2.3741	-1.6189	5.0478	4.2926
3.0000	3.0000	1.3154	-1.0650	5.6017	5.3513

Choose controller TYPE : Pro,D,I, PI,PD, PID, lag, lead ,lead integral :




Fig. 4(a) analyzing open and closed loop system response, closed loops system's responses to step ramp and parabolic inputs




Fig. 4(a) closed loop system response, in terms of output speed and angle when PD controller is selected for $K_p=K_d=[1 \ 2 \ 3]$

Running the proposed built-in function for given motor parameters and choosing Lead compensator with gains, for simplicity, $K_c = [1 \ 2 \ 3]$, $Z = [1 \ 2 \ 3]$ and $P = [1 \ 2 \ 3]$, will return the up mentioned information, mainly compensator closed transfer function for each time each value of three vectors is substituted, as well as the response plots shown in Figure 5




Fig. 5 response of PMDC motor when lead compensator is applied with the following different gains, poles and zeros : $K_c = [1 \ 2 \ 3]$, $Z = [1 \ 2 \ 3]$ and $P = [1 \ 2 \ 3]$,

Running the proposed built-in function for given motor parameters and choosing PID controller with gains

$K_P = [1 \ 2 \ 3]$, $K_I = [1 \ 2 \ 3]$, $K_D = [1 \ 2 \ 3]$, will return PID, and closed transfer function for each time each value of three vectors is substituted, will return the mentioned results and plots shown in Figure 6.




Fig. 6 response of PMDC motor when PID Controller is applied with $K_P = [1 \ 2 \ 3]$, $K_I = [1 \ 2 \ 3]$, $K_D = [1 \ 2 \ 3]$,

To verify design, calculations and built in function results, the proposed simulink for given motor parameters and choosing PID controller with gains e.g. $K_P = [1]$, $K_I = [1]$, $K_D = [1]$, is used.

7. The set of MATLAB new proposed built-in function instructions:

```
function pmdc

% PMDC Used for a given PMDC Analysis and controller selection and
evaluation of
% a given PMDC motor desired output Angle OR Speed
% There is no input argument, the function is called by by
typing its name
% User is required to Define used PMDC motor parameters &
desired output Data
% Then select controller for performance analysis and design
% Author : Dr Farhan Atallah Salem AbuMahfouz
% Ddate : 10/02/2000
%
clear all ;close all; clc
disp(' ')
fprintf(' -----\n')
fprintf(' Analysis and controller selection and
```

```

evaluation of \n')
fprintf('          a given PMDC motor output Angle OR Speed :-
Program \n')
fprintf(' -----\n')
fprintf('          Define used PMDC motor parameters & desired
output Data: \n')
fprintf(' =====\n')

% Vin= 12;Jm=0.02;bm =0.03;Kt =0.023; Kb=0.023 ;Ra =1;La=0.23; TL =
0;max_angle=180;max_speed=6.6667 ;Kpot =0.0667 ;Ktach=1.8;

Jm = input(' Enter moment of inertia of the rotor, (Jm) =');
bm = input(' Enter damping constant of the mechanical system , (bm)=');
Kt = input(' Enter torque constant, Kt=');
Kb = input(' Enter electromotive force constant, Kb=');
Ra = input('Enter electric resistance of the motor armature (ohms), Ra
=');
La =input(' Enter electric inductance of the motor armature (Henry),
La=');
Vin = input(' Enter Max. applied input voltage, Vin = ');
max_angle=input(Enter Max. required output angle = ');
max_speed=input(Enter Max. required output speed = ');
linear_speed=input(' Enter desired robot linear speed ');

Kpot=Vin/max_angle;
Ktach= Vin/max_speed;

num1 = [1];den1= [La ,Ra];num2 = [1];den2= [Jm ,bm];
A = conv( [La ,Ra], [Jm ,bm]); TF1 =tf(Kt, A);
G_speed= feedback(TF1,Kb),G_angle=tf(1,[1,0] )*G_speed,
fprintf(' =====\n')
fprintf(' PMDC Motor parameters: Jm= %g, bm=%g, Kt=%g,Ra=%g,La=%g,Desired
angle=%g,Desired speed=%g : \n', Jm,bm,Kt,Ra,La,max_angle,max_speed)
home

fprintf(' ----- \n')

disp(' Jm bm Kt Ra La Desired output Desired output Kpot Ktach
')
disp(' angle speed
')
fprintf(' %g %g %g %g %g %g %g %g %g \n ',
Jm,bm,Kt,Ra,La,max_angle,max_speed,Kpot,Ktach)

disp(' -----')
disp(' -----')

G_open_motor_num=[Kt];
G_open_motor_speed_den= [La*Jm, (Ra*Jm+bm*La), (Ra*bm+Kt*Kb)];
G_open_motor_angle_den=[La*Jm, (Ra*Jm+bm*La), (Ra*bm+Kt*Kb), 0];
t1=input('Enter time vector for output speed response :');%t1=0:0.001:6;

```

```

t2=input('Enter time vector for angle output response :');%0:0.001:150;

fprintf(' =====\n')
disp(' ')
fprintf('    Open loop transfer function of original PMDC motor system
relating Vin & angle:\n ')
fprintf('    G(s) = ''Theta''(s)/Vin(s)=\n ')
G_open_motor_angle=tf(Kt,[La*Jm, (Ra*Jm+bm*La), (Ra*bm+Kt*Kb), 0])

fprintf('    The closed loop Transfer function of PMDC motor system
relating Vin & angle:\n ')

T_close_motor_angle=feedback(G_open_motor_angle,Kpot)
fprintf(' =====\n')
fprintf(' =====\n')
disp(' ')
fprintf('    Open loop transfer function of original PMDC motor system
relating Vin & speed :\n ')
fprintf('    G(s) = ''Omega''(s)/Vin(s)=\n ')

G_open_motor_speed=tf(Kt,[La*Jm, (Ra*Jm+bm*La), (Ra*bm+Kt*Kb)])

disp(' ')
fprintf('    The closed loop transfer function of PMDC motor system
relating Vin & speed :\n ')
fprintf('    T(s) = ''Omega''(s)/Vin(s)=\n ')
T_closed_motor_speed=feedback(G_open_motor_speed, Ktach)

fprintf(' =====\n')
fprintf(' -----
\n')
subplot(4,3,2) ,step(Vin*G_open_motor_angle,t2),
title(' Open loop PMDC motor system ,step ANGLE response '),
ylabel('Output Angle '), xlabel('Time')
subplot(4,3,5) ,step(Vin*G_open_motor_speed,t1),
title(' Open loop PMDC motor system ,step SPEED response '),
ylabel('Output Speed'), xlabel('Time')

% output CLOSED loop angle response
u = t2; u1 = t2 ;u2 = t2.*t2;
[y,x] = step(T_close_motor_angle,t2);
subplot(4,3,7) ,plot(t2,y,t2,15 ),
xlabel('Time'), ylabel('Error amplitude')
title(' CLOSED angle Step response')
% [yy,xx] = lsim(T_close_motor_angle,u1,t2);
% subplot(4,3,8) ,plot(t2,yy,t2,u1)
subplot(4,3,8), lsim(T_close_motor_angle,u1,t2);
xlabel('Time'), ylabel(' ') %ylabel('Error amplitude')
title(' CLOSED angle Ramp response')

```



```

[yyy,xxx] = lsim(T_close_motor_angle,u2,t2);
subplot(4,3,9) ,plot(t2,yyy,t2,u2)
xlabel('Time'), %ylabel('Error amplitude')
title(' CLOSED angle Parabolic response')

% output CLOSED loop speed response
uu = t1; uu1 = t1 ;uu2 = t1.*t1;
[N,M] = step(T_closed_motor_speed,t1);
subplot(4,3,10) ,plot(t1,N,t1,0.32 ),
xlabel('Time'), ylabel('Error amplitude')
title(' CLOSED speed Step response')
% [NN,MM] = lsim(T_closed_motor_speed,uu1,t1);
% subplot(4,3,11) ,plot(t1,NN,t1,uu1)
subplot(4,3,11), lsim(T_closed_motor_speed,uu1,t1);

xlabel('Time'), %ylabel('Error amplitude')
title('CLOSED speed Ramp response')

[NNN,MMM] = lsim(T_closed_motor_speed,uu2,t1);
subplot(4,3,12) ,plot(t1,NNN,t1,uu2)
xlabel('Time'), %ylabel('Error amplitude')
title('CLOSED speed Parabolic response')
quit=1;
while quit~=0
    disp(' ')

fprintf('=====\n');
    controller=input('Choose controller TYPE : Pro,D,I, PI,PD, PID, lag,
lead ,lead integral :', 's');
fprintf(' -----\n')
    home
    disp(' '),disp(' ')

    zz=lower (controller);
    switch (zz)
        case 'pro'
            Kp=input(' Enter proportional gain values in row vector form, Kp = ');%
            Kp =[ 1 5 8 ];
            Ess_step=zeros(1,length(Kp));
            angle_max=zeros(1,length(Kp));
            angle_end=zeros(1,length(Kp));
            for i=1:length(Kp)
                Q=1:length(Kp);
                G_close_P_speed= feedback(Kp(i)*G_open_motor_speed,Ktach);
                G_close_P_angle = feedback(Kp(i)*G_open_motor_angle,Kpot);
                y1(:,i)=step(Vin*G_close_P_speed,t1);
                y2(:,i)=step(Vin*G_close_P_angle,t2);
                %pause(1)
            end
        end
    end
end

```

```

        yA(:,i)=step(Vin*G_close_P_angle,t2.*1000);
        angle_endA(Q(i))= yA(end);
        angle_max(Q(i))= max(y2(:,i));
        Ess_step(Q(i))= 1/(1+ dcgain(Kp(i).*G_open_motor_angle));
        Ess(i) = max_angle - angle_end(Q(i));
        Mp(i)= angle_max(Q(i))- max_angle;
        yB(:,i)=step(Vin*G_close_P_speed,t1.*1000);
        speed_endA(Q(i))= yB(end);
        speed_max(Q(i))= max(y1(:,i));
        Ess1_step(Q(i))= 1/(1+ dcgain(Kp(i).*G_open_motor_speed));
        Ess1(i) = max_speed - speed_endA(Q(i));
        Mp1(i)= speed_max(Q(i))- max_speed;
    end
figure, subplot(2,1,1),plot(t1,y1(:,1:length(Q)));
title('Closed loop Step response, output SPEED '),ylabel(' Output
SPEED'),xlabel('Time')
    C = regexp(sprintf('Kp=%d#', Kp), '#', 'split'); C(end) = [];
legend( C ),
    ylabel(' Output speed'),
    subplot(2,1,2),plot(t2,y2(:,1:length(Q))), legend(C )
    title('Closed loop Step response, output ANGLE '),ylabel('
Output angle'),xlabel('Time')
    %figure, sisotool(Kp(i)*G_close_P_speed)
    fprintf(' \n');

fprintf('=====\n');
fprintf('For chosen Kp, the following ANGLE RESPONSE SPEC. results are
obtained: \n');
fprintf('=====\n');
fprintf('      Gain      Error      (Mp)      max value      Final \n');
fprintf('      Kp      (Ess)      (Mu)      (Peak)      output \n');
fprintf('-----\n')
answers= [Kp'      Ess'      Mp'      angle_max'      angle_endA' ];
disp(answers )

fprintf('=====\n');
fprintf('=====\n');
fprintf('For chosen Kp, the following SPEED RESPONSE SPEC. results are obtained: \n');
fprintf('=====\n');
fprintf('      Gain      Error      (Mp1)      max value      Final \n');
fprintf('      Kp      (Ess1)      (Mu1)      (Peak)      output \n');
fprintf('=====\n');
answers= [Kp'      Ess1'      Mp1'      speed_max'      speed_endA' ];
disp(answers )
fprintf('=====\n');
    case 'd'
Kd =input(' Enter Derivative gain values in row vector form Kd = ');%[700
750 800];
    Ess_step=zeros(1,length(Kd));
    angle_max=zeros(1,length(Kd));

```

```

angle_end=zeros(1,length(Kd));
for i=1:length(Kd)
    Q=1:length(Kd);
    G_d=[Kd(i) 0];
    numa=G_d*Kt;
    G_open_D_speed=tf(numa,G_open_motor_speed_den );
    G_open_D_angle=tf(numa,G_open_motor_angle_den );
    G_close_D_speed=feedback(G_open_D_speed,Ktach);
    G_close_D_angle=feedback(G_open_D_angle,Kpot)
    y1(:,i)=step(Vin*G_close_D_speed,t1);
    y2(:,i)=step(Vin*G_close_D_angle,t2);

    % calculating output Angle response specification
    yA(:,i)=step(Vin*G_close_D_angle,t2.*100);
    angle_end(Q(i))= y2(end);
    angle_endA(Q(i))= yA(end);
    angle_max(Q(i))=max(y2(:,i));
    Ess_step(Q(i))= 1/(1+ dcgain(Kd(i).*G_open_D_angle));
    Ess(i) =max_angle - angle_endA(Q(i)) ;
    Mp(i)= angle_max(Q(i))- max_angle;

    % calculating output Speed response specification

    yB(:,i)=step(Vin*G_close_D_speed,t1.*1000);
    speed_endA(Q(i))= yB(end);
    speed_max(Q(i))= max(y1(:,i));
    Ess1_step(Q(i))= 1/(1+ dcgain(Kd(i).*G_open_motor_speed));
    Ess1(i) = max_speed - speed_endA(Q(i));
    Mp1(i)= speed_max(Q(i))- max_speed;
end

subplot(2,1,1),plot(t1,y1(:,1:length(Q)));title('Step response, output
SPEED '),ylabel(' Output SPEED'),xlabel('Time')
C = regexp(sprintf('Kd=%d#', Kd), '#', 'split'); C(end)=[]; legend( C ),
subplot(2,1,2),plot(t2,y2(:,1:length(Q))), legend(C ), title('Step
response, output ANGLE '),ylabel(' Output angle'),xlabel('Time')
fprintf(' \n');

fprintf('=====\n');
fprintf('For chosen Kd, the following ANGLE RESPONSE SPEC. results are
obtained: \n');
fprintf('=====\n');
fprintf(' Gain Error (Mp) max Ouput Final \n');
fprintf(' Kd (Ess) Peak value output \n');
fprintf('=====\n');
answers= [Kd' Ess' Mp' angle_max' angle_endA' ];
disp(answers )

fprintf('=====\n');

```

```

fprintf('=====\n');
fprintf('For chosen Kp, the following SPEED RESPONSE SPEC. results are
obtained: \n');
fprintf('=====\n');
fprintf('    Gain      Error      (Mp1)    max value      Final \n');
fprintf('    Kp        (Ess1)    (Mul)     (Peak)        output \n');
fprintf('=====\n');
        answers= [Kd'      Ess1'   Mp1'     speed_max'   speed_endA' ];
        disp(answers )
fprintf('=====\n');
        case 'i'
Ki =input(' Enter Derivative gain values in row vector form Ki =
'),%[0.009   1   3];
        Ess_step=zeros(1,length(Ki));
        angle_max=zeros(1,length(Ki));
        angle_end=zeros(1,length(Ki));

for i=1:length(Ki)
        Q=1:length(Ki);
        num_G_I=[Ki(i)];
        den_G_I=[1   0];
        G_I=tf(num_G_I,den_G_I);
        G_open_I_speed_num=conv(num_G_I,G_open_motor_num);
        G_open_I_speed_den=conv(den_G_I,G_open_motor_speed_den);
G_open_I_speed =tf(G_open_I_speed_num,G_open_I_speed_den );
        G_open_I_angle_num=conv(num_G_I,G_open_motor_num);
        G_open_I_angle_den=conv(den_G_I,G_open_motor_angle_den);
        G_open_I_angle =tf(G_open_I_angle_num,G_open_I_angle_den );
        G_close_I_speed=feedback(G_open_I_speed,Ktach);
        G_close_I_angle=feedback(G_open_I_angle,Kpot);

        % calculating output Angle response specification

        y1(:,i)=step(Vin*G_close_I_speed,t1);
        y2(:,i)=step(Vin*G_close_I_angle,t2);
        %pause(1)
        yA(:,i)=step(Vin*G_close_I_angle,t2.*100);
        angle_end(Q(i))= y2(end);
        angle_endA(Q(i))= yA(end);
        angle_max(Q(i))=max(y2(:,i));
        Ess_step(Q(i))= 1/(1+ dcgain(Ki(i).*G_open_I_angle));
        Ess(i) =max_angle - angle_endA(Q(i)) ;
        Mp(i)= angle_max(Q(i))- max_angle;

        % calculating output speed response specification
yB(:,i)=step(Vin*G_close_I_speed,t1.*1000);
        speed_endA(Q(i))= yB(end);
        speed_max(Q(i))= max(y1(:,i));

```

```

    Ess1_step(Q(i))= 1/(1+ dcgain(Ki(i).*G_open_I_speed));
    Ess1(i) = max_speed - speed_endA(Q(i));
    Mp1(i)= speed_max(Q(i))- max_speed;

    end
    subplot(2,1,1),plot(t1,y1(:,1:length(Q)));
    title('Step response, output SPEED '),ylabel(' Output
SPEED'),xlabel('Time')
C=regexp(sprintf('Kd=%d#', Ki), '#', 'split');
C(end)=[];legend(C ),subplot(2,1,2),plot(t2,y2(:,1:length(Q))),
legend(C ), title('Step response, output ANGLE '),ylabel(' Output
angle'),xlabel('Time'), format short, fprintf(' \n');

fprintf('=====\n');
fprintf('For chosen Ki, the following ANGLE response spec. results are
obtained: \n');
fprintf('=====\n');
fprintf('    Gain      Error      (Mp)    max output      Final \n');
fprintf('    Ki        (Ess)          Peak value      output \n');
fprintf('=====\n');
answers= [Ki'    Ess_step'    Mp'    angle_max'    angle_endA' ];
disp(answers )

fprintf('=====\n');
fprintf('=====\n');
fprintf('For chosen Kp, the following SPEED response spec. results are
obtained: \n');

fprintf('=====\n');
fprintf('    Gain      Error      (Mp1)    max value      Final \n');
fprintf('    Kp        (Ess1)    (Mul)    (Peak)        output \n');
fprintf('=====\n');
answers= [Ki'    Ess1'    Mp1'    speed_max'    speed_endA' ];
disp(answers )

fprintf('=====\n');
fprintf('    The I-controller has the unique ability to return \n')
fprintf('    the process back to the exact setpoint that is eliminating
\n')
fprintf('    the error, but it has a disadvantage based on fact that
integration \n')
fprintf('    is a continual summing. Integration of error over time means
summing \n')
fprintf('    up the complete controller error history up to the present
time, this means\n')
fprintf('    I-controller can initially allow a large deviation at the
instant the error is \n')
fprintf('    produced. This can lead to system instability and cyclic
operation \n')

```

```

        case 'pd'
Kp =input('Enter Proprtinal gain values in row vector form Kp = ');%[1,
1.5 , 1.8703 ];
Kd=input('Enter Derivative gain values in row vector form Kd =
');%[ 1,2,3.336 ]
    Ess_step=zeros(1,length(Kd));
    angle_max=zeros(1,length(Kd));
    angle_end=zeros(1,length(Kd));
    for i=1:length(Kp)
        Q=1:length(Kp);
        for ii=1:length(Kd)
            G_PD=Kd(i)*[1 ,Kp(i)/Kd(ii)];
            num=conv(G_PD ,Kt );
G_open_PD_speed=tf (num,[La*Jm, (Ra*Jm+bm*La), (Ra*bm+Kt*Kb)]);
G_open_PD_angle=tf (num,[La*Jm, (Ra*Jm+bm*La), (Ra*bm+Kt*Kb), 0]);
            G_close_PD_speed=feedback(G_open_PD_speed,Ktach);
            G_close_PD_angle=feedback(G_open_PD_angle,Kpot);
            y1(:,i)=step(Vin*G_close_PD_speed,t1);
            y2(:,i)=step(Vin* G_close_PD_angle,t2);
            %pause(1)

            yA(:,i)=step(Vin.*G_close_PD_angle,t2.*1000);
            angle_end(Q(i))= y2(end);
            angle_endA(Q(i))= yA(end);
            angle_max(Q(i))=max(y2(:,i));
            Ess_step(Q(i))= 1/(1+dcgain(Kd(i).*G_open_PD_angle));
            Ess(i) =max_angle - angle_endA(Q(i)) ;
            Mp(i)= angle_max(Q(i))- max_angle;

% calculating output speed response specification
            yA1(:,i)=step(Vin.*G_close_PD_speed,t1.*1000);
            speed_end(Q(i))= y1(end);
            speed_max(Q(i))=max(y1(:,i));
            speed_endA(Q(i))= yA1(end);

            Ess_step(Q(i))= 1/(1+dcgain(Kd(i).*G_open_PD_speed));
            Ess1(i) =max_speed - speed_endA(Q(i)) ;
            Mp1(i)= speed_max(Q(i))- max_speed;
        end
    end

subplot(2,1,1),plot(t1,y1(:,1:length(Q)));title('Step response, output
SPEED '),ylabel(' Output SPEED'),xlabel('Time'),
C=regexp(sprintf('Kp=%g#, Kd=%g#', Kp,Kd), '#', 'split');
C(end)=[];legend(C),
subplot(2,1,2),plot(t2,y2(:,1:length(Q))), legend(C ),title('Step
response, output ANGLE '),ylabel(' Output angle'),xlabel('Time')
fprintf(' \n');

```

```

fprintf('=====\n');
fprintf('For chosen Kp,Kd the following ANGLE RESPONSE SPEC. results are
obtained: \n');
fprintf('=====\n');
fprintf('    Gain      Gain      Error      (Mp)      max Output
Final \n');
fprintf('    Kp      Kd      (Ess)      Peak value
output \n');
fprintf('=====\n');
answers= [Kp'      Kd'      Ess'      Mp'      angle_max'      angle_endA' ];
disp(answers )

fprintf('=====\n');
fprintf('=====\n');
fprintf('For chosen Kp,Kd the following ANGLE RESPONSE SPEC. results are
obtained: \n');

fprintf('=====\n');
fprintf('    Gain  Gain  Error  (Mp1)  max value  Final \n');
fprintf('    Kp   Kd   (Ess1)  (Mul)   (Peak)    output \n');

fprintf('=====\n');
aanswers= [ Kp'      Kd'      Ess1'      Mp1'      speed_max'
speed_endA' ];
disp(aanswers )
fprintf('=====\n');
case 'lead'
Kc =input('Enter Lead gain values in row vector form Kc =
');;%[34,300,450 ];
Z=input('Enter Lead zero value , Z = ');;%[ 1.5410];
P=input('Enter Lead Pole value , P = '); ;[%[15.410]
Ess_step=zeros(1,length(Kc));
angle_max=zeros(1,length(Kc));
angle_end=zeros(1,length(Kc));
figure
for i=1:length(Kc)
    for ii=1:length(Z)
        for iii=1:length(P)
            Q=1:length(Kc);
            num_lead= Kc(i).*[ 1 Z(ii)];
            den_lead= [ 1 P(iii)];
            disp(' Lead Transfer function : ')
            G_lead=tf(num_lead,den_lead)
            G_open_lead_speed=series (G_lead ,G_open_motor_speed);
            G_open_lead_angle=series (G_lead ,G_open_motor_angle);
disp(' Closed loop Transfer function, SPEED/Vin= : ')
            G_close_lead_speed=feedback(G_open_lead_speed,Ktach)
disp(' Closed loop Transfer function, ABLE/Vin= : ')
            G_close_lead_angle=feedback(G_open_lead_angle,Kpot)

```

```

        y1(:,iii)=step(Vin*G_close_lead_speed,t1);
        y2(:,iii)=step(Vin*G_close_lead_angle,t2);
        % pause(1)
        yA(:,iii)=step(Vin*G_close_lead_angle,t2.*1000);
        plot(t1,y1(:,1:length(Kp)))
        hold on
        title('Step response, output ANGLE '),ylabel(' Output
ANGLE'),xlabel('Time'),C=regexp(sprintf('Kc=%d# P=%d# Z=%d#', Kc,P,Z), '#',
'split'); C(end)=[];legend(C ),

        angle_end(iii)= y2(end);
        angle_endA(iii)= yA(end);
        angle_max(iii)=max(y2(:,iii));
        Ess_step(iii)= 1/(1+ dcgain(Kc(i).*G_close_lead_angle));
        Ess(iii) =angle_max(iii) - angle_endA(iii) ;
        Mp(iii)= angle_max(iii)- max_angle;
                                end
        end
    case 'lead integral'
        Kc =input('Enter Lead-Integral gain values in row vector form Kc
= ');%[4 7 30 ];
        Z=input('Enter Lead-Integral zero , Z = ');%[ 0.15410];
        P=input('Enter Lead-Integral Pole , P = '); %[1.5410];
        Ess_step=zeros(1,length(Kc));
        angle_max=zeros(1,length(Kc));
        angle_end=zeros(1,length(Kc));

        for i=1:length(Kc)
            Q=1:length(Kc);
            num_lead= Kc(i)*[ 1 Z];
            den_lead_integral= conv([1 0],[ 1 P]);
            G_lead_integral=tf(num_lead,den_lead_integral);
            G_open_controller_speed=series
(G_lead_integral ,G_open_motor_speed)
            G_open_controller_angle=series
(G_lead_integral ,G_open_motor_angle)

            G_close_controller_speed=feedback(G_open_controller_speed,Ktach);

            G_close_controller_angle=feedback(G_open_controller_angle,Kpot)
            y1(:,i)=step(Vin*G_close_controller_speed,t1);
            y2(:,i)=step(Vin*G_close_controller_angle,t2);
            %pause(1)
            yA(:,i)=step(Vin*G_close_controller_angle,t2.*1000);
            angle_end(Q(i))= y2(end);
            angle_endA(Q(i))= round(yA(end));
            angle_max(Q(i))=max(y2(:,i));
            Ess_step(Q(i))= 1/(1+ dcgain(Kc(i).*G_open_controller_angle));
            Ess(i) =max_angle - angle_endA(Q(i)) ;
            Mp(i)= angle_max(Q(i))- max_angle;

```



```

end
subplot(2,1,1),plot(t1,y1(:,1:length(Q)));
title('Step response, output SPEED '),ylabel(' Output
SPEED'),xlabel('Time')
C = regexp(sprintf('Kd=%d#', Kc), '#', 'split'); C(end) = []; legend( C ),
subplot(2,1,2),plot(t2,y2(:,1:length(Q))), legend(C )
title('Step response, output ANGLE '),ylabel(' Output
angle'),xlabel('Time')
fprintf(' \n');
fprintf('=====\n');
fprintf('For chosen Kc the following ANGLE RESPONSE SPEC. results are
obtained: \n');
fprintf('=====\n');
fprintf(' Gain Error (Mp) max Output Final \n');
fprintf(' Kc (Ess) Peak value output \n');
fprintf('=====\n');
answers= [Kc' Ess' Mp' angle_max' angle_endA' ];
disp(answers )
fprintf('=====\n');
case 'PI'
Ki=input('Enter Integral gain Ki = ');%[ 0.01];
Kp=input('Enter Proprtrional gain Kp = ');% [9];
Z =[Ki/Kp];
num_PI=Kp*[1 Z];
den_PI=[ 1 0];
G_PI =tf(num_PI,den_PI)
G_open_PI_speed_num=conv(num_PI,Kt)
G_open_PI_speed=series(G_PI,G_open_motor_speed)
G_open_PI_angle=series(G_PI,G_open_motor_angle)
G_close_speed=feedback(G_open_PI_speed,1);
G_close_angle=feedback(G_open_PI_angle,Kpot)
subplot(2,1,1),step(Vin*G_close_speed);
title('Step response, output speed '),
[a,b]=step(Vin*G_close_angle,t1);
subplot(2,1,2), plot(t2,a), title('Step response, output angle ')
[yA,b]=step(Vin*G_close_angle,t2.*100);
angle_end= yA(end);
angle_endA = round(yA(end)) ;
angle_max = max(yA);
Ess =max_angle - angle_endA ;
Mp = angle_max - max_angle;
fprintf(' \n');
fprintf('=====\n');
fprintf('For chosen Kp,Ki, the following ANGLE RESPONSE SPEC. results
are obtained: \n');
fprintf('=====\n');
fprintf(' Gain Error (Mp) max output Final \n');
fprintf(' Kp Ki (Ess) Peak value output \n');
fprintf('=====\n');
answers= [Kp' Ki' Ess' Mp' angle_max' angle_endA' ];
disp(answers )
fprintf('=====\n'); case 'lag'
Kc =input('Enter lag compensator gain values in row vector form Kc = ');%[4 7
30 ];

```

```

Z=input('Enter lag zero , Z = ');%[ 0.13410];
P=input('Enter lag Pole , P = '); %[0.013410]
for i=1:length(Kc)
    Q=1:length(Kc);
    num_lag= Kc(i)*[ 1 Z];
    den_lag= [ 1 P];
    G_lag=tf(num_lag,den_lag);
    G_open_lag_speed=series (G_lag ,G_open_motor_speed)
    G_open_lag_angle=series (G_lag ,G_open_motor_angle)
    G_close_lag_speed=feedback(G_open_lag_speed,Ktach);
    G_close_lag_angle=feedback(G_open_lag_angle,Kpot)
    y1(:,i)=step(Vin*G_close_lag_speed,t1);
    y2(:,i)=step(Vin*G_close_lag_angle,t2);
    %pause(1)
    yA(:,i)=step(Vin*G_close_lag_angle,t2.*100);
    angle_end(Q(i))= y2(end);
    angle_endA(Q(i))= round(yA(end));
    angle_max(Q(i))=max(y2(:,i));
    Ess_step(Q(i))= 1/(1+ dcgain(Kc(i).*G_open_lag_angle));
    Ess(i) =max_angle - angle_endA(Q(i)) ;
    Mp(i)= angle_max(Q(i))- max_angle;
end
subplot(2,1,1),plot(t1,y1(:,1:length(Q)));
title('Step response, output speed '),
C = regexp(sprintf('Kc=%d#', Kc), '#', 'split');
C(end) = []; legend( C ),
ylabel(' Output angle')
subplot(2,1,1),plot(t2,y2(:,1:length(Q)));
title('Step response, output angle ')
legend( C ), ylabel(' Output angle'),xlabel('Time')
fprintf(' \n');
fprintf('=====\n');
fprintf('For chosen Kc, the following ANGLE RESPONSE SPEC. results are obtained:
\n');
fprintf('=====\n');
fprintf(' Gain Error (Mp) max output Final \n');
fprintf(' Kc (Ess) Peak value output \n');
fprintf('=====\n');
answers= [Kc',Ess', Mp' angle_max',angle_endA' ];
disp(answers )
fprintf('=====\n');
case 'pid'
Kp=input('Enter PID Proportional gain Kp =');%150 ;
Ki=input('Enter PID Integral gain Ki =');%11
Kd =input('Enter PID Derivative gain values in row vector form Kd =
');;%[50 75 140];
% Z1=[ 4.3069]; Z2= [0.15410];
for i=1:length(Kp)
    for ii=1:length(Ki)
        for iii=1:length(Kd)
            Q=1:length(Kd);
            num_PID= Kd(iii)*[1 Kp(i)/Kd(iii) Ki(ii)/Kd(iii)]
            den_PID= [ 1 0];
            G_PID=tf(num_PID,den_PID);

```

```

G_open_PID_speed=series (G_PID ,G_open_motor_speed);
G_open_PID_angle=series (G_PID ,G_open_motor_angle);
G_close_PID_speed=feedback(G_open_PID_speed,Ktach);
G_close_PID_angle=feedback(G_open_PID_angle,Kpot)
y1(:,i)=step(Vin*G_close_PID_speed,t1);
y2(:,i)=step(Vin*G_close_PID_angle,t2);
pause(1)
angle_end(Q(i))= y2(end);
angle_max(Q(i))=max(y2(:,i));
Ess_step(Q(i))= 1/(1+ dcgain( G_open_PID_angle));
yA(:,i)=step(Vin*G_close_PID_angle,t2.*100);
angle_end(Q(i))= y2(end);
angle_endA(Q(i))= round(yA(end));
angle_max(Q(i))=max(y2(:,i));
Ess_step(Q(i))= 1/(1+ dcgain(Kd(i).*G_open_PID_angle));
Ess(i) =max_angle - angle_endA(Q(i)) ;
Mp(i)= angle_max(Q(i))- max_angle;
                                end
                                end
                                end
                                plot(t1,y1(:,1:length(1)))
hold on, title('Step response, output ANGLE '),ylabel(' Output
ANGLE'),xlabel('Time')
C=regexp(sprintf('Kp=%d# Ki=%d# Kd=%d#', Kp,Ki,Kd), '#', 'split');
C(end)=[];legend(C ),subplot(2,1,1),plot(t1,y1(:,1:length(Q)));
title('Step response, output speed '),
C = regexp(sprintf('Kp=%d# Kd=%d# Ki=%d#', Kd,Ki,Kp), '#', 'split'); C(end) = [];
legend( C ),ylabel(' Output angle'),
subplot(2,1,2),plot(t2,y2(:,1:length(Q)));title('Step response, output angle '),
legend( C ), ylabel(' Output angle'),xlabel('Time ')
fprintf(' \n');

fprintf('=====\n');
fprintf('For chosen Kp=%d Ki=%d and Kd=%d, the following ANGLE
RESPONSE SPEC. results are obtained: \n', Kp ,Ki, Kd);
fprintf('=====\n');
fprintf(' Gain      Error      (Mp)  max output      Final \n');
fprintf('      Kd      (Ess)      Peak Value      output \n');
fprintf('=====\n');
answers= [Kd',Ess', Mp' ,angle_max',angle_endA' ];
disp(answers ), fprintf('=====\n');
otherwise
home, disp( ' '), fprintf('=====\n');
fprintf('      Such controller is not considered here \n');
fprintf('      Please choose only one of controller listed \n ');
fprintf('=====\n');
quit=input(' DO YOU WANT TO RUN PROGRAM ONCE AGAIN, ( 1 or 0 ):');
end
end
home
disp(' ')
fprintf('=====\n');
fprintf(' Thank you, you can send your comments to salem_farh@yahoo.com\n')
fprintf('=====\n');

```

pause (3)
home

8. Conclusion

A new MATLAB built-in function, mathematical and simulink models are proposed and tested, all designed to be simultaneously simple, user-friendly and to be used to face the two top challenges in developing mechatronic motion control systems, as well as, performance analysis and verification of a given electric DC system, proper controller selection and verification for desired output speed or angle.

The simulink model and new built in function were test for desired output speed , angle and chosen control strategy, results show the applicability , simplicity of use and acceleration of the design process while maintain accuracy.

References

- [1] D'Azzo, John Joachim, Houpis, Constantine H, "Linear control system analysis and design: conventional and modern", 1988.
- [2] Hedaya Alasooly, "Control of DC motor using different control strategies" global journal of technology and optimization 2011.
- [3] Farhan A. Salem ; Mechatronics motion control design of electric motor for desired deadbeat response specifications, supported and verified by new MATLAB built-in function and simulink model , submitted , in 2012, to Int. J. Intelligent Systems Technologies and Applications.
- [4] Ahmad Atallah Salem, Mohamed M. K, Farhan A. Salem, PMDC motor Modeling simulation and analysis using different methods and verification by MATLAB/Simulink. submitted and accepted, but not published yet, to International Journal of Intelligent Systems and Applications(IJISA) ; paper ID 123.
- [5] Richard C. Dorf, Robert H. Bishop, Modern Control Systems 12 Ed, Pearson Education, Inc., 2001.
- [6] Hedaya alasooly, "PhD thesis: Control and Modeling of Facts devices and Active Filters on Power System", Electrical Energy Department, Czech Technical University, 2003, published in www.lulu.com.
- [7] Ahmad A. Mahfouz, Ayman A. Aly, Farhan A. Salem, "Mechatronics Design of a Mobile Robot System", IJISA, vol.5, no.3, pp.23-36, 2013.
- [8] Chun Htoo Aung, Khin Thandar Lwin, and Yin Mon Myint, Modeling Motion Control System for Motorized Robot arm using MATLAB, World Academy of Science, Engineering and Technology 42 2008.
- [9] MathWorks, 2001, Introduction to MATLAB, the MathWorks, Inc. Control System Toolbox, the MathWorks, Inc.

Authors' Profiles



Ahmad Atallah Mahfouz: B.Sc. and M.Sc; Bari University, Italy and Moscow state Academy. Now, He is ass. Professor in Automatic and Mechatronics Systems, Vladimir State University and the director of alpha centre for engineering studies and technology researches. Major academic and research interests: Design, modelling and analysis of primary Mechatronics Machines, Control Systems, Robotics, Electronics, Microcontrollers, and Quantity Surveying.



Farhan Atallah Salem: B.Sc., M.Sc and Ph.D., in Mechatronics of production systems, Moscow state Academy. Now he is ass. Professor in Taif University, Mechatronics program, Dept. of Mechanical Engineering and gen-director of alpha centre for engineering studies and technology researches. Research Interests; Design, modelling and analysis of primary Mechatronics Machines, Control selection, design and analysis for Mechatronics systems. Rotor Dynamics and Design for Mechatronics applications

How to cite this paper: Ahmad A. Mahfouz, Farhan A. Salem, "Performance Analysis, Controller Selection And Verification Of Electric Motor For Mechatronics Motion Control Applications, Using New MATLAB Built-In Function And Simulink Model", IJEM, vol.3, no.2, pp.11-39, 2013. DOI: 10.5815/ijem.2013.02.02